

Portable emergency luminaire W270.4/8

W270.4/8



Portable luminaire W270.4/8 with emergency light function

- Very bright with 2 x 8 W LEDs with CRI 80 for good color rendering
- 8000 mAh lithium-ion battery for up to 24 hours of emergency light or 6 hours of operation at 100%
- Five lighting modes: narrow-beam spotlight and work light in two power levels and additional blinking function for signaling purposes. An orange diffuser is housed in the luminaire head
- Swiveling luminaire head reinforced with a solid aluminum ring and ergonomically aligned, rubberized handle



Narrow beam

With the narrow-beam reflector and a beam angle of 11°, the portable luminaire is suitable as a searchlight with a range of up to 210 m (according to ANSI/NEMA FL1) or for illuminating an area from a great distance.



Wide beam

The wide-beam reflector provides uniform light (beam angle 65°), making it suitable for use as a work light. The wide-beam light distribution is also used for the emergency light function, helping with orientation for up to 24 hours, e.g., in the electrical operating room.



Charge status

The charging cradle with integrated LED light bar clearly indicates the charge status



● Green = Fully charged



● Red = Charging



● Orange =
Return the luminaire to the charger

★ **Blinking orange** =
A power interruption has occurred since the luminaire was removed (see EN60598-2-22 E.7.12).

EATON

Powering Business Worldwide


Features



- With the selectable blinking function and the included orange diffuser, the portable luminaire is also suitable as a warning light for hazard areas.
- The diffuser is always stored within easy reach on the back of the portable luminaire.



- The emergency lighting function enables the luminaire to switch on in the event of a power failure, providing immediate safety lighting.
- For maximum runtime, the switch should be adjusted to 24h-15%.
- This setting provides 140 lumen - sufficient brightness to ensure safe movement.



- The user-friendly rotary knob is safe and easy to operate even with gloves.
- Three LEDs next to the switch provide information about the battery's charge status at all times.

Ordering details



Type	Scope of delivery	Order No.
W270.4/8	Portable luminaire with emergency lighting function, including charging cradle, power supply and orange diffuser	40071357340



Wall mount bracket	This bracket firmly holds the charging cradle, with a Velcro strap that secures the luminaire while allowing easy access. Its mounting points are compatible with earlier models like the "Wall bracket" for CEAG W276.3 and "Charger Z345.3" for CEAG W270.3.	40071357341
--------------------	--	-------------



Car charger	Adaptor to supply the charging cradle with 12/24V in a car or truck.	40071357346
-------------	--	-------------

Eaton
EMEA Headquarters
Route de la Longeraie 7
1110 Morges, Switzerland
Eaton.eu

CEAG Notlichtsysteme GmbH
Senator-Schwartz-Ring 26
59494 Soest, Germany
Tel.: +49 (0) 2921 69-870
Fax: +49 (0) 2921 69-617
Email: info-n@ceag.de
Website: www.eaton.com